

Specifications

| | |
|--------------------|-------------------------------------|
| Input Impedance | 1M Ohm |
| Input Channels | 6 High/Low level Selectable |
| Input Options | High Level or Low Level |
| Input Type | Differential-Balanced |
| Input Voltage | 0 - 28v Peak to Peak |
| High Level Range | |
| Input Voltage | 0 - 4.9v Peak to Peak |
| Low Level Range | |
| | |
| Output Channels | 10 |
| Output Voltage | Up to 5v RMS |
| Output Impedance | 50 Ohms |
| Equalizer Type | 31 Band Graphic EQ, +/- 10dB |
| THD | <0.03% |
| Frequency Response | 20Hz - 20kHz |
| Crossover | 3-Way LPF, BPF, HPF THP per channel |
| Crossover Type | Linkwitz-Riley 24DB Slope, Fixed |
| Sampling | 48kHz |
| S/N Ratio | 105dB @ 5V RMS |

General

| | |
|------------------------|---|
| Operating Voltage | 10 - 16VDC |
| Standby Current Draw | ~7mA |
| Operation Current Draw | ~150mA |
| Adjustments/Controls | Application via Bluetooth |
| Remote Output | 12VDC, Signal Sense or with Ignition |

Product Info



Having difficulties? We're here to help.



Contact our Tech Support line at:
386-257-1187



Or via email at:
techsupport@metra-autosound.com

Tech Support Hours (Eastern Standard Time)

Monday - Friday: 9:00 AM - 7:00 PM

Saturday: 10:00 AM - 7:00 PM

Sunday: 10:00 AM - 4:00 PM



KNOWLEDGE IS POWER

Enhance your installation and fabrication skills by enrolling in the most recognized and respected mobile electronics school in our industry. Log onto www.installerinstitute.com or call 800-354-6782 for more information and take steps toward a better tomorrow.



**Metra recommends MECP
certified technicians**