

marantz



SR5015

Marantz SR5015 7.2ch 8K AV receiver with HEOS® Built-in and Voice Control

Drive exquisitely detailed home cinema with the Marantz SR5015 7.2 channel 8K UHD AV receiver. Delight in the most musical sound for any source — from home theater, to vinyl, to digital streaming. Totally immerse yourself in movies and TV with elevated surround sound formatting from Dolby Atmos® and DTS:X®. Enjoy seamless voice control from the leading voice agents, multi-room connectivity and the latest in HDMI technology.

- Performance, power and connectivity to suit your audio preferences: 7.2 channel discrete power amplifier, 100W per channel (8 Ohm, 20Hz-20kHz, THD: 0.08%, 2ch. drive).
- 8K/60Hz and 4K/120Hz pass-through support for every entertainment need: With the latest technology in HDMI support, enjoy 8K quality video from your 8K source devices. 8K upscaling is available on all 6 HDMI ports.
- Support for the most advanced object-based audio formats: Dolby Atmos®, Dolby Atmos Height Virtualization Technology, DTS:X® and DTS Virtual:X™ processing are all supported to allow you to listen to immersive, multi-dimensional audio.
- Enhanced Audio Return Channel (eARC) HDMI support: Through the main HDMI output, connect your TV with eARC HDMI support to allow uncompressed and object-based audio formats like Dolby Atmos® and DTS:X® directly from a smart TV app to your AV receiver.
- Bringing you the latest in video compatibility: Support for the latest HDR formats including HDR10, HDR10+ (New in 2020), HLG, Dolby Vision, 4:4:4 color resolution and BT.2020, as well as Dynamic HDR (New in 2020) provides exceptional picture quality for brightness, clarity and contrast.
- The greatest technology for home cinema: With 8K/60Hz pass-through or upscaling, Dynamic HDR and Quick Media Switching (QMS), enjoy crystal clear picture and accurate detail.
- Advanced gaming specifications: With 4K/120Hz pass-through, Variable Refresh Rate (VRR), Auto Low Latency Mode (ALLM) and Quick Frame Transport (QFT), experience gaming thrills with amazing imaging and reduced lag.
- High-resolution streaming for audiophile approved sound: Ability to decode ALAC, FLAC and WAV lossless files up to 24-bit/192-kHz; DSD 2.8MHz and 5.6MHz tracks — enjoy your music exactly as the artist intended.
- Exclusive components elevate Marantz sonic signature: Marantz proprietary HDAM circuit boards, Current Feedback circuitry, AKM AK4458 32-bit D/A converters, and Hybrid PLL Clock Jitter Reducer produce more detailed, dynamic sound.
- Stream music from your favorite sources: Play songs from Spotify, Pandora, TIDAL and more via AirPlay 2, Bluetooth, Wi-Fi and HEOS® Built-in.

Modern Musical Luxury



SR5015

Technical Specs



Multichannel surround		
DTS HD Master / DTS:X / DTS:X Pro		• / • / -
DTS Neo:X / DTS Neural:X		- / •
DTS Virtual:X		
IMAX Enhanced		-
Dolby TrueHD / Dolby Atmos / Dolby Atmos Height Virtualization		• / • / •
Dolby ProLogic Iiz / Dolby Surround		- / •
Auro 3D		-
Multichannel Stereo		
Max Number of Processing (Preamp) Channels		7.1
Sound Enhancements		
Discrete Power Amplifier		•
Copper Plated Chassis		-
Power Transformer: Toroidal / EI		EI
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24		• / • / •
Current Feedback Topology		•
Hyper Dynamic Amplifier Modules (HDAM)		•
Pure Direct		•
Gold Plated RCA Terminals		-
Clock Jitter Reducer		-
Audyssey		MultEQ XT
Audyssey Dynamic EQ / Dynamic Volume		• / •
Audyssey LFC		-
Compressed Audio Enhancer: MDAX2		•
Network		
HEOS Multi-room and Streaming		•
Bluetooth Re-transmit for Bluetooth headphones		•
Alexa / Google Voice Assistant / Apple HomePod		• / • / •
Network Audio Sharing		•
Lossy Formats: MP3 / WMA / AAC		• / • / •
Lossless Formats: FLAC / ALAC / WAV		• / • / •
Lossless formats: FLAC HD 192/24 / WAV 192/24 / ALAC 192/24		• / • / •
DSD Audio Streaming		• (2.8/5.6MHz)
FLAC HD 192/24		•
WAV 192/24		•
ALAC 192/24		•
Gapless Playback		• (FLAC, WAV, ALAC, DSD)
AirPlay Audio Streaming		• (AirPlay2)
Internet Radio		• (TuneIn)
Spotify*		• (connect)
Pandora		•
SiriusXM		•
Other Streaming Services *		Amazon Music HD / TIDAL / Deezer / iHeart Radio / Napster / Soundcloud / Mood Mix
Compatible with Remote APP for Smart Phones		Marantz 2016 AVR Remote
Compatible with Remote APP for Tablets		Android / iOS / Amazon Kindle
Ethernet Ports		•
Wi-Fi		•
Bluetooth		•
HDMI		
HDMI Inputs: Back / Front		6 / 0
HDCP2.3 support		•
HDMI Outputs: Main / Zone		2 / -
Video Conversion Analog -> HDMI		•
Analog to HDMI scaling		480i/576i up to 8K 60/50
HDMI to HDMI scaling		up to 8K 60/50
GUI Overlay on HDMI		•
8K/60Hz / 4K/120Hz		• / •
3D / 4K / CEC / ARC		• / • / • / -
Enhanced ARC		•
HDR / HLG / Dolby Vision / HDR10+ / Dynamic HDR		• / • / • / • / •
ALLM (Auto Low Latency Mode) Pass-through for gaming		•
Variable Refresh Rate / Quick Flame Transport / Quick Media Switching		• / • / •
3D Signal Pass-Through		•
8K signal pass-through / scaling / GUI overlay		• / • / •
4K Signal Pass-Through / Scaling / GUI Overlay		• / • / •
HDMI Pass-Through in Standby Mode		•
Picture Adjust / Noise Reduction		• / •
CEC		•
DSD Audio Capability		-
Audio Return Channel		•
Auto LipSync		•

Multiroom / CI		
HEOS Multi-Room Integrated		•
HEOS Link Compatibility: IR/ IP		• / •
Multi-Room zones		2
Zone Audio Source: HDMI / Opt, Coax / Network, USB / Analog		• (2ch) / • (2ch) / • / •
Zone Audio Output: Speaker / Preout		• / •
Zone HDMI Output from HDMI Source		-
IP Control / RS232 Control / Web Control / App Control		• / • / • / •
IR Flasher In		•
Marantz Remote Bus		•
DC Trigger Output		1
HDMI Diagnostics		•
Others		
Auto Speaker Setup by Microphone		Audyssey MultEQ XT
FL Display		Port Hole
Graphic User Interface - GUI		Advanced
ISF Certification		•
GUI Languages		3
Setup Assistant		•
Smart Select		•
Firmware Update by Network / USB		• / •
Variable Cross Over		•
Optimized Bass Redirection		•
Bass Sync		-
ECO Mode		•
Auto Power Off		•
Sleep Timer		•
Video Inputs/Outputs		
Composite In / Out		2+1 / 1
Component In / Out		2 / 1
HDMI In / Out		6 / 2
Multi-Room Video Out: Video / HDMI		- / -
Audio Inputs/Outputs		
Analog In / Out		4+1 / -
Phono (MM) In		•
Digital In: Optical / Coaxial		2 / 2
Multi-Room Out: Analog / Digital		1 / -
Multichannel Pre Out		• (7.2)
Subwoofer Out		2
7.1 Multichannel Input		-
Other		
Speaker Terminal: Gold Plated Screw / Regular Screw		- / •
Number of Speaker Terminals		7
Speaker A / B		assignable
Bi-Amp Drive		assignable
Multi-Room Speaker Terminal		assignable
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB		• / • / - / - / •
USB Audio / Made for iPod / Made for iPhone		• / - / -
AM/FM Tuner		•
General Power		
Number of Poweramps		7
Power Output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch Drive)		100 W
Power Output (6 ohm, 1 kHz, 0.7% 2ch Drive)		140 W
Power Output (6 ohm, 1 kHz, 10% 1ch Drive)		200 W
70% Guarantee		•
General		
Metal Front Panel		-
System Remote Control		RC042SR
Pre-Programmed / Learnable / LCD Display		- / - / -
Power Consumption in W		650
Power Consumption No-Sound (ECO on / off) in W		45 W / 75 W
Standby Consumption in W		0.2
CEC Standby Consumption in W		0.5
Network Standby Consumption in W		2.7
Maximum Dimensions		
Antenna/Horizontal:(W x D x H)		17.3 x 13.7 x 6.3
Antenna/Vertical:(W x D x H)		17.3 x 13.7 x 9.1
w/o Antenna:(W x D x H)		17.3 x 13.3 x 6.3
Weight in LBS		22.3

Design and specifications are subject to change by Marantz without notice.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.