

- ▲ Step-up
- ◆ New

- 130 Watts Total: 65 Watts per Channel x 2
- ▲ ◆ New Slim Style Main Unit (20cm width)
  - Huge 16cm Woofer
  - 3 Disc CD Changer
  - CD-R/RW<sup>1</sup> with MP3 Playback Capability
  - Line In for Digital Music Player or PC
  - 2-Way Bass Reflex Speaker System
  - DSGX Bass Boost Function
  - Digital AM/FM Stereo Tuner
  - 4 Preset EQ Settings



**MP3**



## Features

- ◆ 130 Watts Total Power 65 Watts per Channel x 2
- New Slim Style Main Unit with 20cm width easily fits into any room.
- 16cm Woofer fills any room with powerful sound
- 3 Disc CD Changer provides an easy way to keep the music going all day or all night.
- ◆ CD-R/CD-RW<sup>1</sup> with MP3 Playback Capability Plays back MP3 files recorded onto CD-R/RW discs.
- Line In for Digital Music Player or PC allows for simple plug-and-play integration with a digital music player or PC via a 3.5 mm jack.
- 2-Way Bass Reflex Speaker System A type of speaker enclosure that includes a "tuned" port to increase and extend bass response by releasing some of the energy created by the inward movement of the woofer cone.
- DSGX Bass Boost Function Increases the Bass to fill any room with powerful sound.
- Digital AM/FM Stereo Tuner Provides accurate, drift-free tuning of AM and FM stations and lets you choose from a wide variety of radio, talk and music programming with the added enjoyment of stereo sound.
- 4 Preset EQ settings Creates enhanced sound modes for different types of music, such as rock and pop.

## Specifications

### General

Type of Use: Shelf System  
 Tray Type: Tray Loading 3 Disc CD Changer with Play Exchange (Semiconductor Laser 780nm)  
 Disc Capacity: 3

### Audio

Digital-to-Analog Converter: 1 Bit  
 Frequency Response: CD: 20-20000Hz (±0.5dB); Cassette: 50-13000Hz (±0.3dB)  
 Format(s) Supported: CD-DA, CD-R/RW, CD's WITH MP3 Playback Capability<sup>1</sup>  
 Tuning: Auto Scan Radio  
 Antenna System: AM: Loop Antenna, FM: Lead Antenna  
 Frequency Range: AM: 530-1710kHz; FM: 87.5-108.0MHz  
 CD Play Mode(s): Program, Shuffle, Repeat  
 Station Preset(s): 30 (10 AM, 20 FM)  
 Sound Enhancer: Groove Bass Boost Function, Virtual Surround Sound Mode  
 Equalizer: 9 Presets (Rock, Pop, Jazz, Dance, Soul, Oriental, Reggae, Salsa, Samba), 3 Personal File Settings  
 Tuner Type: FM/AM Superheterodyne Tuner

### Convenience Features

Timer Events: Record/Play/Sleep (Wake-up or Fall Asleep To Music-Select from 10 Timed Shut Offs)  
 Power Save Mode: Yes

### Hardware

Display: LCD  
 Remote Control: Yes (Remote Commander®)

### Power

Power Requirements: AC 120V, 60Hz  
 Output Power: 130 Watts Total: 65 Watts per Channel x 2 (RMS 10% THD, 120-10 kHz)  
 Power Consumption: 205W

Manual: 210W

Battery Type: Remote: "AA" x 2

Power Handling Capacity: With 6 ohms loads, both channels driven from 120-10000 Hz; rated 150 W per channel-minimum RMS power, with no more than 10% total harmonic distortion from 250 milliwatts to rated output.

### Speaker

Speaker System: 2 Way Bass Reflex Type  
 Speaker Dimensions: 2" (5cm)  
 Woofer Size(s): 6.3" (16cm)

### Inputs and Outputs

Analog Audio Input(s): 1 (Rear, Stereo Mini)  
 Headphone Input(s): 1 (Front, Stereo Mini)  
 PC Audio Input(s): Yes  
 Antenna Terminal (AM Loop): 1 (Rear)  
 Antenna Terminal (FM 75 Ohm): 1 (Rear)

### Dimensions

Weight: Speaker: 8 lbs 6 oz (3.8 Kg) (each x 2); Main Unit: 22 lbs 1 oz (10 Kg)  
 Measurements: Speaker: W 9 1/16" x H 13 7/12" x D 9 1/4" (230 x 345 x 235mm) (each x 2); Main Unit: W 11" x H 12 4/5" x D 16 13/14" (280 x 325 x 430mm)

### Supplied Accessories

Instruction Manual  
 Remote Commander® Remote Control (RM-SC50)  
 AM Loop Antenna  
 FM Lead Antenna

UPC Code: 027242705777

1. CD-R/RW media/formats are not universally compatible.

© 2007 Sony Electronics Inc.  
 Reproduction in whole or in part without written permission is prohibited. All rights reserved. Sony, Remote Commander, and like no other are trademarks of Sony.  
 Features and specifications are subject to change without notice. Non-metric weights and measures are approximate.

Please visit the Dealer Network for current information at [www.sony.com/dn](http://www.sony.com/dn)