

High-Performance Home Theater Receiver offering many advanced functions including 1080p-compatible HDMI, XM and SIRIUS Satellite Radio ready, iPod and Bluetooth compatibility, CINEMA DSP, YPAO sound optimization, and four SCENE buttons.




























8 CINEMA DSP Programs







- 4 SCENE buttons offering greater operating ease (with 17 preset SCENE templates)
- XM ready with XM HD Surround powered by Neural Surround
- SIRIUS Satellite Radio ready
- YPAO for automatic speaker setup
- iPod compatibility via Yamaha Universal Dock
- Bluetooth (A2DP) compatibility with Yamaha Bluetooth® Wireless Audio Receiver (YBA-10)
- Front panel mini jack for connecting portable audio player
- On-screen display with iPod song title display
- **High Sound Quality**
 - 5-channel 525W powerful surround sound (105W x 5)
 - Direct mode for high quality sound reproduction
 - Burr-Brown 192kHz/24-bit DACs used in all channels
- High Picture Quality
 - 1080p-compatible HDMI (2 in/1 out) including 1080p/24Hz repeat
 - HDTV compatible component video terminals (3 in/1 out)
- Surround Realism
 - CINEMA DSP with 8 DSP programs
 - Compressed Music Enhancer to improve compressed music sources
 - Night Listening Enhancer (Cinema/Music) and SILENT CINEMA

Compatible Decoder Straight Dolby Digital DTS Digital Surround Dolby Pro Logic Dolby Pro Logic II Music Dolby Pro Logic II Movie Dolby Pro Logic II Game Neural Surround **CINEMA DSP Programs** Pop/Rock MUSIC Hall lazz Game ENTERTAINMENT TV Sports Movie Spacious MOVIE STEREO 5ch Stereo CINEMA DSP Program Total 8





SCENE — Greater Operating Ease

Four SCENE buttons make operating the receiver easier than ever. Pressing a SCENE button automatically turns the power on and launches a number of operations that initiate play of the source controlled by that button. Many SCENE settings are available, such as Dock Listening, DVD Viewing, Radio Listening and Game Playing. Browsing and selecting the settings is quickly accomplished by rotating the Input knob and watching the on-screen display. The SCENE names can be changed also.



XM Satellite Radio Ready with XM HD Surround Powered by Neural Surround

This receiver is XM Satellite Radio Ready, allowing you to hear over 170 digital channels of music, news, sports, talk and entertainment. To get XM Satellite Radio the XM Mini-Tuner and Home Dock including home antenna are required.

This receiver is also capable of receiving XM Satellite Radio with XM HD Surround powered by Neural Surround.

SIRIUS Satellite Radio Ready

The RX-V463BL is also ready to receive SIRIUS satellite radio. SIRIUS brings your favorite entertainment straight into your home, including 100% commercial-**SIRIUS** free music, plus superior sports coverage, uncensored talk and comedy, exclusive entertainment, world-class news and more.

YPAO for Automatic Speaker Setup

The RX-V463BL uses Yamaha's YPAO system that quickly and automatically analyzes the acoustics of the room and adjusts various speaker parameters to provide the optimum sound at the listening position. It's like having a professional audio engineer set up and tweak your system.

Initial Volume and Maximum Volume

Two volume settings are included on this receiver for additional convenience. Initial Volume Setting allows you to set the volume level that will be heard each time the power is turned on. Maximum Volume Setting prevents unexpected loud sounds, for example if a young child turns the volume knob

High Sound Quality

Direct Mode

You can enjoy pure HiFi sound from 2-channel PCM and analog sources by the Direct mode which allows signals to bypass the decorders and DSP processors.

High Dynamic Power Capability

The RX-V463BL receiver is capable of delivering large amounts of reserve power for accurate reproduction of the high energy peaks that are especially prevalent in digital audio sources. This prevents clipping and emphasizes the music's dynamic qualities.

Audio-Grade Parts and Devices

The RX-V463BL offers the latest and best technologies, parts and circuit designs to

maximize sound quality. These include custommade block capacitors (1), high





grade Burr-Brown DACs and ADC (2) and other high quality audio-grade parts.

High Picture Quality

1080p-Compatible HDMI (2 In/1 Out)

This receiver features dual HDMI inputs and one output that support 1080p resolution so users can connect two HDMI sources, such as a DVD player and a high definition set-top box, and enjoy the highest possible quality with a 1080p display. With 1080p/24Hz signal repeating, you can enjoy the full potential of Blu-ray discs.

HDTV Compatible Component Video Terminals (3 In/1 Out)

Component Video inputs offer higher picture quality, for use with units such as DVD players that have Component Video output. You can enjoy three different sources without having to change connections. The frequency response of the component video signal is 5Hz - 60MHz, making it compatible with HDTV (1080i/720p)

Surround Realism

CINEMA DSP with 8 DSP Programs

You have a choice of eight unique Yamaha CINEMA DSP surround programs to bring out the full audio potential of your entertainment sources.


Compressed Music Enhancer

When music is encoded in a digital compressed

0 0 0 0 0 0 0 O HDMI XM / SIRILIS Satellite Radio Terminal Analog A/V / Audio 1/1 Dock Terminal (for iPod / Bluetooth) Component Video Monitor Optical Digital (Fixed and Assignable) Composite Monitor Coaxial Digital (Fixed and Assignable) Analog A/V / Audio* Speaker (without subwoofer) 5 ch / 7 ter. 4/2 Subwoofer Component Video

6 ch

format such as MP3, frequency response suffers in the high and low ranges. Yamaha employs sophisticated digital signal processing with exclusive algorithms, enabling faithful reproduction of the original music, for excellent sound quality.



The Compressed Music Enhancer restores the original live sound of your music, especially deep, strong sounds like bass and drums

Night Listening Enhancer and SILENT CINEMA

The Night Listening Enhancer offers two modes, Cinema and Music, with three-level selectability, which will ensure that you don't miss movie dialogue or quiet passages, or lose overall surround spaciousness even during low volume listening late at night.

The SILENT CINEMA mode allows private listening enjoyment of multi-channel music or movies, with an accurate simulation of surround sound, through ordinary headphones.

Other Notable Features

- 40-station preset tuning / Auto preset tuning HD Audio LPCM 5.1-channel reception (up to
- 96kHz)
- iPod song titles displayed in English and Western European languages ISO 8859-1 (Latin 1) on the front panel and on-screen
- display Virtual CINEMA DSP
- Audio Delay for adjusting lip-sync (0-160ms)
- 9 selectable subwoofer crossover frequencies
- Subwoofer phase select
- Dolby Digital, DTS and Dolby Pro Logic II decoding
- Front panel Video Aux input with mini jack
- Subwoofer out
- 6-channel external input
- Speaker A or B selection Preset remote unit
 - Yamaha Bluetooth® Wireless Audio Receiver

The YBA-10 Bluetooth Audio Receiver docks to the receiver and supports A2DP audio streaming, so users can enjoy music wirelessly from Bluetoothenabled mobile phones, Windows PCs and Macs



Yamaha Universal Dock for iPod

The optional Yamaha Universal Dock lets you connect your iPod to the receiver.





Main Specifications

iPod not included

Minimum RMS Output Power (8 ohms, 1 kHz, 0.9% THD) Front L/R Channels 105 W/ch Center Channel 105 W Surround L/R Channels
Dynamic Power (1 kHz) 105 W/ch 8/6/4/2 ohms 110/130/160/180 W Frequency Response 10 Hz-100 kHz +0, -3 dB Total Harmonic Distortion (CD, Front Sp Out) (1 kHz, 50 W/8 ohms) 100 dB (250 mV) Signal-to-Noise Ratio (CD) Monitor Out Frequency Response Component Video Signal 5 Hz-60 MHz -3 dB 17¹/₈° x 5¹⁵/₁₆° x 13⁷/₈° 435 x 151 x 352 mm 18.7 lbs.; 8.5 kg Dimensions (W x H x D)

• The XM Satellite Radio service is only available in the 48 contiguous United States (not available in Alaska and Hawaii) and Canada. • XM name, XM Ready and related logos are registered trademarks of XM Satellite Radio, Inc. • Neural Surround™ name and related logos are trademarks owned by Neural Audio Corporation. • "SIRIUS" and the SIRIUS dog logo are registered trademarks of SIRIUS Satellite Radio Inc. • IPOS in a trademark of Popple, Inc., registered trademarks of DTS, Inc. • The Manual Surround* are registered trademarks of DTS, Inc. • HDMI, the HDMI logo and High-Definition Multimedia Interface are trademarks or registered trademarks of HDMI Licensing LLC. • Burr-Brown products are trademarks of Texas instruments inc. • The Bulletoith® word mark and logos are registered trademarks owned by Bluetooth SIG. Inc. • CINEMA DSP is a trademark of Yamaha Corporation. • SILENT CINEMA is a trademark of Yamaha Corporation. • Product designs and specifications are subject to change without notice.

Multi-Channel External Input * Including front panel Video Aux terminals.